

200mmの場合は
取付できません。
「Wターミナル板付」
をご利用ください。

パリア

M6ねじ取付用穴

定格感度電流切替装置

動作時間切替装置

漏電表示ボタン

テストボタン

68 (中幅)

42 (左右幅)

t 8

t 8

遮断器外形

☆バネ付カット

82

194

R3

4-M6
又はφ7穴

44

137

7

103

97

30

133

110

135

62

12

24

90

181

225

257

301

333

φ11穴

130

110 (中導)

85

65 (左側板)

取付番

スタッド取付方向A方式
(標準仕様)

スタッド取付方向B方式
(常法仕様)

絶縁チューブ (中導)

225

143

110

65

130

194

225

284 (含7mmハン)

6-φ35穴

4-M6又はφ7穴

5

44

44

44

44

絶縁板取付時不要

発熱高少用みぞ

通断器外形

穴寸法

ベーススタッド方向標準 (A方式) で出荷します

[illegible]

動作特性曲線

The graph shows the operating time of a 200A circuit breaker under various current conditions. The y-axis represents time in seconds on a logarithmic scale from 0.001 to 100. The x-axis represents current in amperes on a logarithmic scale from 100 to 5000. Three curves are shown: a solid line for the maximum breaking time, a dashed line for the maximum closing time, and a solid line for the time at 400A. The 200A curve shows a long time delay (up to 100s) for currents between 100A and 1200A, followed by a sharp drop to approximately 0.02s for currents above 1200A.

電流 (A)	動作時間 (秒) - 最大全遮断時間 (実線)	動作時間 (秒) - 最大全遮断時間 (点線)	動作時間 (秒) - 400A設定の場合 (実線)
100	100	100	100
1200	100	100	100
1500	0.02	0.02	0.02
2000	0.02	0.02	0.02
4000	0.02	0.02	0.02