



欠相サーマルリレー(2E) ●電動機の過負荷・欠相保護用

型式	適合電動機容量(kW)		ヒータ仕様		仕様区分	ご注文品番	メーカー希望小売価格(円)	復帰方式	単独取付	重量(kg)
	3φ 200V	3φ 400V	中心値(A)	調整範囲(A)						
TR20-2E			0.2	0.16~0.24	●	USM01	4,980	手動 自動 兼用	可能	0.14
			0.3	0.24~0.36	●	USM02				
			0.4	0.32~0.48	●	USM03				
			0.5	0.4~0.6	●	USM04				
			0.6	0.5~0.7	●	USM05				
			0.8	0.7~0.9	●	USM06				
			1.0	0.8~1.2	●	USM07				
	0.2	0.4	1.2	1.0~1.4	●	USM08				
			1.4	1.1~1.7	●	USM10				
		0.75	1.8	1.4~2.2	●	USM11				
	0.4		2.4	2.0~2.8	●	USM12				
			3.0	2.4~3.6	●	USM13				
	0.75	1.5	3.8	3.0~4.5	●	USM14				
		2.2	5.0	4.0~6.0	●	USM15				
	1.5	3.7	6.8	5.5~8.0	●	USM16				
	2.2		9.0	7.0~11	●	USM17				
		5.5	11	9~13	●	USM18				
	3.7	7.5	15	12~18	●	USM20				
	5.5	11	20	16~24	●	USM21				
TR40-2E	2.2		9.0	7.0~11	●	USP17	8,760	手動 自動 兼用	可能	0.25
		5.5	11	9~13	●	USP18				
	3.7	7.5	15	12~18	●	USP20				
	5.5	11	20	16~24	●	USP21				
	7.5	15	28	22~34	●	USP23				
	11	18.5	40	32~48	●	USP24				
	15	30	55	45~65	●	USP25				
TR100-2E	5.5	11	20	16~24	●	USS21	10,400	手動 自動 兼用	可能	0.36
	7.5	15	28	22~34	●	USS23				
	11	18.5	40	32~48	●	USS24				
	15	30	55	45~65	●	USS25				
	18.5	37	67	55~80	●	USS26				
	22	45	80	65~95	●	USS27				
	30	55	105	90~120	●	USS28				
	37	75	130	110~150	●	USS30				

■標準サーマルリレー、欠相サーマルリレー

一とも定格使用電流が150Aを超える場合、サーマルリレーとCTの組合せとなります。

■銘板

