

## AC400V級

(Sym : kA)

| 主幹用配線用遮断器        |                | B-223WB | B-403WA | B-603WA | B-803WB | B-1003WA | B-1203WA | B-1603WA | B-2003W | B-2503W |
|------------------|----------------|---------|---------|---------|---------|----------|----------|----------|---------|---------|
| 分岐用<br>配線用遮断器    | 定格遮断容量<br>(kA) | 50      | 50      | 50      | 50      | 85       | 85       | 85       | 85      | 85      |
|                  |                |         |         |         |         |          |          |          |         |         |
| B-33EC           | 2.5            | 2.5     | 2.5     | 2.5     | 2.5     | 2.5      | 2.5      | 2.5      | 2.5     | 2.5     |
| B-53EC           | 2.5            | 2.5     | 2.5     | 2.5     | 2.5     | 2.5      | 2.5      | 2.5      | 2.5     | 2.5     |
| B-53S<br>B-63S   | 5              | 3       | 4       | 5       | 5       | 5        | 5        | 5        | 5       | 5       |
| B-53FEA          | 7.5            | 4       | 4       | 7.5     | 7.5     | 7.5      | 7.5      | 7.5      | 7.5     | 7.5     |
| B-53FD<br>B-63FA | 10             | 4       | 4       | 7.5     | 7.5     | 10       | 10       | 10       | 10      | 10      |
| B-53FKA          | 50             | 4       | 4       | 7.5     | 7.5     | 50       | 50       | 50       | 50      | 50      |
| B-63EC           | 2.5            |         | 2.5     | 2.5     | 2.5     | 2.5      | 2.5      | 2.5      | 2.5     | 2.5     |
| B-103EC          | 5              |         | 4       | 5       | 5       | 5        | 5        | 5        | 5       | 5       |
| B-103S           | 22             |         |         | 7       | 7       | 18       | 20       | 22       | 22      | 22      |
| B-103FB          | 25             | 4       | 4       | 7.5     | 7.5     | 25       | 25       | 25       | 25      | 25      |
| B-103FKA         | 50             | 4       | 4       | 7.5     | 7.5     | 35       | 50       | 50       | 50      | 50      |
| B-123EC          | 7.5            |         | 4       | 6       | 6       | 7.5      | 7.5      | 7.5      | 7.5     | 7.5     |
| B-153EC          | 7.5            |         |         | 6       | 6       | 7.5      | 7.5      | 7.5      | 7.5     | 7.5     |
| B-223EA          | 18             |         |         | 3       | 4       | 15       | 18       | 18       | 18      | 18      |
| B-223S           | 25             |         | 4       | 4       | 4       | 18       | 20       | 25       | 25      | 25      |
| B-223FC          | 30             |         | 4       | 7.5     | 7.5     | 22       | 22       | 30       | 30      | 30      |
| B-253EA          | 18             |         |         | 3       | 4       | 15       | 18       | 18       | 18      | 18      |
| B-403EA          | 25             |         |         |         |         | 7        | 8        | 25       | 25      | 25      |
| B-403FB          | 50             |         |         |         | 7.5     | 18       | 22       | 22       | 30      | 30      |
| B-603EA          | 22             |         |         |         |         |          | 22       | 22       | 22      | 22      |
| B-603FA          | 50             |         |         |         |         |          | 22       | 22       | 30      | 30      |
| B-803FA          | 35             |         |         |         |         |          |          | 22       | 30      | 30      |
| B-803WB          | 50             |         |         |         |         |          |          | 22       | 30      | 30      |
| B-1003WA         | 85             |         |         |         |         |          |          |          |         | 30      |
| B-1203WA         | 85             |         |         |         |         |          |          |          |         | 30      |

B

配線用遮断器

漏電遮断器

配線用遮断器 漏電遮断器 オプション・資料

内部付属装置 内部付属装置取付仕様

外部付属装置

電動機分岐回路用漏電遮断器 準形遮断器 イレシ

電動機分岐回路用漏電遮断器 時延形漏電遮断器

資料