

外形寸法

穴明寸法図(mm)

接点構成図

端子部寸法(mm)

MP-100N3

※補助接点 4 a 4 b 付の場合は124

主端子 M8ボルト

コイル端子 M3.5

補助端子 M3.5

リセットボタン (ストローク3)

サーマルリレー M3.5

主端子 M8ボルト

寸法: 137, 88.5, 1.6, 100, 96, 33, 5, 35.5, 210, 205, 192.5, 26, 43, 7, 4.9, 79.5, 88.5, 1.6

3-M5

寸法: 7.5, 250, 80

回路図: C1, A1, B1, 11, 12, 13, 1, B3, C2, A2, B2, 21, 22, 23, 2, 4, 6, 98, 96, 95

		電 磁 接点器		サーマルリレー
主回路	端子ねじ	M8ボルト	M8ボルト	
	端子寸法	A	22	27
		B	8	10
C		11	13	
操作回路	端子ねじ	M3.5	M3.5	
	端子寸法	A	7.8	7.8
		B	5	4
C		4.5	4.5	

MP-120N3 MP-150N3

※補助接点 4 a 4 b 付の場合は144

コイル端子 M3.5

主端子 M8ボルト

補助端子 M3.5

リセットボタン (ストローク3)

サーマルリレー M3.5

主端子 M8ボルト

寸法: 3.5, 147.5, 97, 120, 38, 23, 232, 202, 265, 2, 26, 48, 149, 79.5, 88.5, 2.3

3-M6

寸法: 7.5, 250, 100

回路図: C1, C2, 1, 11, 12, 13, A1, B1, B3, B4, 21, 22, 23, 2, 4, 6, 98, 96, 95

		電 磁 接点器		サーマルリレー
主回路	端子ねじ	M8ボルト	M8ボルト	
	端子寸法	A	27	27
		B	10	10
C		9.5	13	
操作回路	端子ねじ	M3.5	M3.5	
	端子寸法	A	7.8	7.8
		B	6	4
C		4.5	4.5	

MP-200N3 MP-250N3

※補助接点 4 a 4 b 付の場合は172

主端子 M10ボルト

コイル端子 M3.5

補助端子 M3.5

リセットボタン (ストローク3)

サーマルリレー M3.5

主端子 M10ボルト

寸法: 3.5, 174.5, 106, 148, 27, 271, 261, 300, 150, 28.5, 167, 74.5, 3.2

4-M8

寸法: 10, 300, 50

回路図: C1, C2, 1, 11, 12, 13, A1, B1, B3, B4, 21, 22, 23, 2, 4, 6, 98, 96, 95

		電 磁 接点器		サーマルリレー
主回路	端子ねじ	M10ボルト	M10ボルト	
	端子寸法	A	37	
		B	12.5	
C		16		
操作回路	端子ねじ	M3.5	M3.5	
	端子寸法	A	7.8	7.8
		B	6	4
C		4.5	4.5	

MP-300N3 MP-400N3

※補助接点 4 a 4 b 付の場合は187

主端子 M12ボルト

コイル端子 M3.5

補助端子 M3.5

リセットボタン (ストローク3)

サーマルリレー M3.5

主端子 M12ボルト

寸法: 5, 200, 120.5, 163, 58, 25, 290, 276, 370, 164, 28.5, 167, 74.5, 3.2

4-M8

寸法: 10, 350, 60

回路図: 50Hz 60Hz, C1, C3, C2, 1, 11, 12, 13, A1, B1, B3, B4, 21, 22, 23, 2, 4, 6, 98, 96, 95

		電 磁 接点器		サーマルリレー
主回路	端子ねじ	M12ボルト	M12ボルト	
	端子寸法	A	44	
		B	15	
C		20		
操作回路	端子ねじ	M3.5	M3.5	
	端子寸法	A	7.8	7.8
		B	6	4
C		4.5	4.5	

型 式	寸 法					取付間隔(最小)(mm)				
						D	E	F	G	H
MP-100N ₃ , MP-120N ₃ MP-150N ₃						25	15	10	10	10
MP-200N ₃ , MP-250N ₃						30	20	10	10	10
MP-300N ₃ , MP-400N ₃						40	30	10	10	10

Diagram of a parallel plate capacitor with a dielectric slab partially inserted. The top plate is connected to a voltage source E , and the bottom plate is grounded. The dielectric slab is partially inserted from the left, with a length p indicated.

A diagram of a rectangular plate with a central circular hole. The plate has a total width of A and a total height of B . The hole has a diameter of C . The hole is centered horizontally and vertically within the plate. The plate is shown with hatching on the left and right sides, indicating it is part of a larger assembly.