

選択遮断方式

AC200V級

(Sym : kA)

主幹用配線用遮断器		B-223W	B-403W	B-603W	B-803WA	B-1003W	B-1203W	B-1603WA	B-2003W	B-2503W B-3203W
分岐用 配線用遮断器	定格遮断容量 (kA)	85	85	85	125	125	125	125	125	125
		2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5
B-33EA	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5
B-53EA	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5
B-53S B-63S	10	4	5	10	10	10	10	10	10	10
B-53FEA	10	4	5	7.5	7.5	10	10	10	10	10
B-53FD B-63FA	35	4	5	10	10	35	35	35	35	35
B-53FKA	85	4	5	14	14	85	85	85	85	85
B-63EA	2.5		2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5
B-103EA	5		5	5	5	5	5	5	5	5
B-103S	50			10	10	18	20	25	30	30
B-103FB	50	4	5	10	10	50	50	50	50	50
B-103FKA	85	4	5	14	14	85	85	85	85	85
B-123EA	10		5	10	10	10	10	10	10	10
B-153EA	10			10	10	10	10	10	10	10
B-223E	18			3	4	18	18	18	18	18
B-223S	50			3	4	18	20	25	30	30
B-223FB	85		4	10	10	35	35	65	85	85
B-253E	18			3	4	18	18	18	18	18
B-403S	50					7	8	25	30	30
B-403FB	85				10	18	22	25	35	35
B-603S	50						22	25	35	35
B-603FA	85						22	25	35	35
B-803FA	85							25	35	35
B-803WA	125							25	35	35
B-1003W	125									35
B-1203W	125									35

■右図に示すA点で短絡事故が発生した場合に、分岐用遮断器が必ず先に遮断動作を完了し、主幹用遮断器は動作に至らないような構成で健全回路への事故波及を避け、停電範囲を最小限にいくとめる遮断方式です。上表の電流値まで選択遮断が可能です。

