




直流負荷への適用

直流負荷の遮断責務は交流負荷に比べ厳しくなりますが、接点を直列接続し適用が可能です。

50A以下

負荷の種類	時定数 L/R(ms)	電圧 DC(V)	直列 接点数	フレームと定格使用電流(A)						接点接続方法
				10HA	20HA	25HA	35HA	50HA		
抵抗負荷 DC1,DC12級	1以下	48	1	13	15	26	30	30		
			2	13	20	26	30	50		
			3	13	20	26	35	50		
		110	1	10	12	15	15	15		
			2	10	15	26	30	35		
			3	13	20	26	35	50		
		220	1	1	1.5	2	2	2		
			2	6	10	15	20	20		
			3	13	15	26	30	35		
直流モータ負荷 DC2,DC4級	15以下	48	1	3	8	10	10	15		
			2	6	15	20	30	35		
			3	13	20	25	35	40		
		110	1	1.5	2	3	3	3		
			2	4	8	10	15	15		
			3	8	15	20	20	20		
		220	1	0.25	0.4	0.4	0.4	0.4		
			2	1.2	2	3	3	3		
			3	4	8	10	10	10		
コイル負荷 DC13級	100以下	48	1	1	3	3	5	5		
			2	5	12	20	20	20		
			3	8	15	20	25	25		
		110	1	0.7	1	1.2	1.5	1.5		
			2	3	3	5	5	5		
			3	4	10	10	15	15		
		220	1	0.2	0.3	0.4	0.4	0.4		
			2	0.6	1.32	1.5	1.5	1.5		
			3	1.5	2	2	2	2		

(注) 性能：開閉頻度1200回／時、電氣的耐久性約50万回の場合の適用を示します。