

リミッタースペースなし／全電力管内向け

主幹 (P.21～22参照) 30A、40A、50A BU-53・1J／75A、100A BU-103・1KA

分岐 (P.13参照) B-1EA／B-2EA



単3 主幹：単3中性線欠相保護付配線用遮断器

分岐回路数 +予備回路数	主幹 (A)	分岐回路 2P/E 2P/E	仕様 区分	型式	露出形		埋込形		外形寸法 (mm)			盤定格 (A)	外形 寸法 図
					ご注文品番	メーカー希望 小売価格 (円)	ご注文品番	メーカー希望 小売価格 (円)	タテ	ヨコ	フカサ		
6+2	30	4	2	● AB3306-2A	AB33062AS	18,400	AB33062AF	24,700	314	364	95	60	
	50			● AB3506-2A	AB35062AS		AB35062AF						
8+0	30	6	2	● AB3308A	AB3308AS	19,800	AB3308AF	26,100	314	364	95	60	
	50			● AB3508A	AB3508AS		AB3508AF						
10+2	30	8	2	● AB3310-2A	AB33102AS	24,200	AB33102AF	30,700	314	432	95	60	
	50			● AB3510-2A	AB35102AS		AB35102AF						
12+0	30	8	4	● AB3312A	AB3312AS	25,600	AB3312AF	32,100	314	432	95	60	448
	50			● AB3512A	AB3512AS		AB3512AF						
14+2	50	10	4	● AB3514-2A	AB35142AS	30,000	AB35142AF	36,700	314	500	95	60	
	75			● AB3714-2A	AB37142AS	38,300	AB37142AF	45,000				100	
	100			● AB31014-2A	AB310142AS	46,100	AB310142AF	52,800				100	
16+0	50	12	4	● AB3516A	AB3516AS	31,400	AB3516AF	38,100	314	500	95	60	
	75			● AB3716A	AB3716AS	39,700	AB3716AF	46,400				100	
	100			● AB31016A	AB31016AS	47,500	AB31016AF	54,200				100	
16+2	50	12	4	● AB3516-2A	AB35162AS	32,700	AB35162AF	39,400	314	534	95	60	
	75			● AB3716-2A	AB37162AS	41,000	AB37162AF	47,700				100	
	100			● AB31016-2A	AB310162AS	47,900	AB310162AF	54,600				100	
18+0	50	14	4	● AB3518A	AB3518AS	34,100	AB3518AF	40,800	314	534	95	60	
	75			● AB3718A	AB3718AS	42,400	AB3718AF	49,100				100	
	100			● AB31018A	AB31018AS	49,300	AB31018AF	56,000				100	
18+2	50	14	4	● AB3518-2A	AB35182AS	34,700	AB35182AF	41,400	314	568	95	60	
	75			● AB3718-2A	AB37182AS	43,000	AB37182AF	49,700				100	
	100			● AB31018-2A	AB310182AS	49,600	AB310182AF	56,300				100	
20+0	50	14	6	● AB3520A	AB3520AS	36,100	AB3520AF	42,800	314	568	95	60	449
	75			● AB3720A	AB3720AS	44,400	AB3720AF	51,100				100	
	100			● AB31020A	AB31020AS	51,000	AB31020AF	57,700				100	
20+2	75	14	6	● AB3720-2A	AB37202AS	45,000	AB37202AF	51,900	314	627	95	100	
	100			● AB31020-2A	AB310202AS	51,300	AB310202AF	58,200				100	
22+0	75	16	6	● AB3722A	AB3722AS	46,400	AB3722AF	53,300	314	627	95	100	
	100			● AB31022A	AB31022AS	52,700	AB31022AF	59,600				100	
22+2	75	16	6	● AB3722-2A	AB37222AS	48,800	AB37222AF	55,800	314	661	95	100	
	100			● AB31022-2A	AB310222AS	55,100	AB310222AF	62,100				100	
24+0	75	18	6	● AB3724A	AB3724AS	50,200	AB3724AF	57,200	314	661	95	100	
	100			● AB31024A	AB31024AS	56,500	AB31024AF	63,500				100	
26+2	75	20	6	● AB3726-2A	AB37262AS	56,800	AB37262AF	64,800	334	729	95	100	
	100			● AB31026-2A	AB310262AS	63,100	AB310262AF	71,100				100	
28+0	75	22	6	● AB3728A	AB3728AS	58,200	AB3728AF	66,200	334	729	95	100	
	100			● AB31028A	AB31028AS	64,500	AB31028AF	72,500				100	
26+6	75	20	6	● AB3726-6A	AB37266AS	62,500	AB37266AF	71,500	334	797	95	100	450
	100			● AB31026-6A	AB310266AS	68,800	AB310266AF	77,800				100	
28+4	75	22	6	● AB3728-4A	AB37284AS	63,900	AB37284AF	72,900	334	797	95	100	
	100			● AB31028-4A	AB310284AS	70,200	AB310284AF	79,200				100	
30+2	75	24	6	● AB3730-2A	AB37302AS	65,300	AB37302AF	74,300	334	797	95	100	
	100			● AB31030-2A	AB310302AS	71,600	AB310302AF	80,600				100	
32+0	75	26	6	● AB3732A	AB3732AS	66,700	AB3732AF	75,700	334	797	95	100	
	100			● AB31032A	AB31032AS	73,000	AB31032AF	82,000				100	

■内線規程1375-1-4で、住宅の電路に漏電遮断器を取り付けることが規定されています。漏電遮断器が組込まれていない分電盤を住宅の電路にご使用される場合、別途主幹又は分岐回路に漏電遮断器を取り付けてください。

■主幹50Aは、40A、60Aも組替対応できます。別途お問合わせください。