

分岐用配線用遮断器の定格電流 (A) の対応関係

AC400V級

(Sym : kA)

主幹用配線用遮断器 分岐用配線用遮断器	定格遮断容量 (kA)	B-223W	B-403W	B-603W	B-803WA	B-1003W	B-1203W	B-1603WA	B-2003W	B-2503W B-3203W
		50	50	50	85	85	85	85	85	85
B-33E	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5
B-53E	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5
B-53S B-63S	5	4	5	5	5	5	5	5	5	5
B-53FE	7.5	4	4	7.5	7.5	7.5	7.5	7.5	7.5	7.5
B-53FC B-63F	10	4	4	7.5	7.5	10	10	10	10	10
B-53FKA	50	4	4	7.5	7.5	50	50	50	50	50
B-63E	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5	1.5
B-103E	2.5		2.5	2.5	2.5	2.5	2.5	2.5	2.5	2.5
B-103S	22			10	10	18	20	22	22	22
B-103FB	25	4	5	7.5	7.5	25	25	25	25	25
B-103FKA	50	4	5	7.5	7.5	35	50	50	50	50
B-123E	7.5		5	7.5	7.5	7.5	7.5	7.5	7.5	7.5
B-153E	7.5		5	7.5	7.5	7.5	7.5	7.5	7.5	7.5
B-223E	10			3	4	10	10	10	10	10
B-223S	25		5	3	4	18	20	25	25	25
B-223FB	30		5	7.5	7.5	22	22	30	30	30
B-253E	10			3	4	10	10	10	10	10
B-403S	25					7	8	25	25	25
B-403FB	50				7.5	18	22	22	30	30
B-603S	22						22	22	22	22
B-603FA	50						22	22	30	30
B-803FA	35							22	30	30
B-803WA	85							22	30	30
B-1003W	85									30
B-1203W	85									30