

# 時延形 / 特殊周波数用

## 時延形漏電遮断器 (動作時間0.3秒 ± 50%)

時延形漏電遮断器は、漏洩電流検知から遮断まで一定の遅れ時間を持たせたものです。

これを上位遮断器として使用することにより、事故回路のみ遮断でき他回路への波及を防止することができます。(漏電選択遮断)

| 適用定格電圧       |               |      | 100-200V(100/200V)の場合 |       |                | 415Vまたは200-415Vの場合(2Pは除く) |             |       |                |
|--------------|---------------|------|-----------------------|-------|----------------|---------------------------|-------------|-------|----------------|
| 型式           | 定格電圧          | 電流   | 100mA                 | 200mA | 感度切替形          | 100mA                     | 200mA       | 500mA | 感度切替形          |
| 経済タイプ        |               |      |                       |       |                |                           |             |       |                |
| GBL-72EA     | 100-200V      | 75A  | ●                     | ●     |                |                           |             |       |                |
| GBL-73EA     | 100-200V、415V | 75A  | ●                     | ●     | ○100/200/500mA | ●(415V)                   | ●(415V)     |       | ●100/200/500mA |
| GBL-102EA    | 100-200V      | 50A  |                       |       |                |                           |             |       |                |
|              |               | 60A  | ●                     | ●     |                |                           |             |       |                |
|              |               | 75A  | ●                     | ●     |                |                           |             |       |                |
|              |               | 100A | ●                     | ●     |                |                           |             |       |                |
| GBL-103EA    | 100-200V、415V | 50A  | ●                     |       |                | ●(415V)                   | ●(415V)     |       | ●100/200/500mA |
|              |               | 60A  | ●                     | ●     | ●100/200/500mA | ●(415V)                   | ●(415V)     |       | ●100/200/500mA |
|              |               | 75A  | ●                     | ●     | ●100/200/500mA | ●(415V)                   | ●(415V)     |       | ●100/200/500mA |
|              |               | 100A | ●                     | ●     | ○100/200/500mA | ●(415V)                   | ●(415V)     |       | ●100/200/500mA |
| GBL-122EA    | 100-200V      | 125A | ●                     | ●     | ●100/200/500mA |                           |             |       |                |
| GBL-123EA    | 200-415V      | 120A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ●100/200/500mA |
|              |               | 125A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ○100/200/500mA |
| GBL-152EA    | 100-200V      | 150A | ●                     | ●     | ●100/200/500mA |                           |             |       |                |
| GBL-153EA    | 200-415V      | 150A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ○100/200/500mA |
| GBL-222EA    | 100-200V      | 125A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 150A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 175A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 200A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 225A |                       |       | ●100/200/500mA |                           |             |       |                |
| GBL-223EA    | 200-415V      | 125A |                       |       |                |                           |             |       | ●100/200/500mA |
|              |               | 150A |                       |       |                |                           |             |       | ●100/200/500mA |
|              |               | 175A |                       |       |                |                           |             |       | ●100/200/500mA |
|              |               | 200A |                       |       |                |                           |             |       | ○100/200/500mA |
| GBL-253EA    | 200-415V      | 250A |                       |       |                |                           |             |       | ○100/200/500mA |
|              |               | 300A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ●100/200/500mA |
|              |               | 350A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ○100/200/500mA |
|              |               | 400A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ●100/200/500mA |
| GBL-403EA    | 200-415V      | 250A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ●100/200/500mA |
|              |               | 300A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ○100/200/500mA |
|              |               | 350A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ●100/200/500mA |
|              |               | 400A |                       |       |                | ●(200-415V)               | ●(200-415V) |       | ○100/200/500mA |
| 単3中性線欠相保護付   |               |      |                       |       |                |                           |             |       |                |
| GBUL-53-1KC  | 100/200V      | 30A  | ●                     |       |                |                           |             |       |                |
|              |               | 40A  | ●                     |       |                |                           |             |       |                |
|              |               | 50A  | ●                     |       |                |                           |             |       |                |
| GBUL-103-1KC | 100/200V      | 50A  |                       |       |                |                           |             |       |                |
|              |               | 60A  | ●                     | ●     |                |                           |             |       |                |
|              |               | 75A  | ●                     | ●     |                |                           |             |       |                |
| GBUL-123-1EA | 100/200V      | 120A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 125A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 150A |                       |       | ●100/200/500mA |                           |             |       |                |
| GBUL-223-1EA | 100/200V      | 125A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 150A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 175A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 200A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 225A |                       |       | ●100/200/500mA |                           |             |       |                |
| GBUL-253-1EA | 100/200V      | 250A |                       |       | ●100/200/500mA |                           |             |       |                |
| GBUL-403-1EA | 100/200V      | 250A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 300A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 350A |                       |       | ●100/200/500mA |                           |             |       |                |
|              |               | 400A |                       |       | ●100/200/500mA |                           |             |       |                |

時延形 / 特殊周波数用 オプション

時延形漏電遮断器価格 ● 本体価格に下記価格をプラスしてください。

| 適用器種    | GB-72EA, 73EA<br>GBU-53-1KC | GB-102EA, 103EA<br>GBU-103-1KC | GB-122EA, 123EA<br>GBU-123-1EA | GB-152EA, 153EA<br>GBU-153-1EA | GB-222EA, 223EA<br>GBU-223-1EA | GB-253EA<br>GBU-253-1EA | GB-403EA<br>GBU-403-1EA |
|---------|-----------------------------|--------------------------------|--------------------------------|--------------------------------|--------------------------------|-------------------------|-------------------------|
| 標準価格(円) | 4,500                       | 4,500                          | 4,500                          | 4,500                          | 4,500                          | 4,500                   | 4,500                   |